

1. Open your web browser and navigate to the URL;
<http://<Device PAP IP>>
 And Enter Supervisor password (Default password: 19750407)
2. For SIP, configure your device as per the following image's highlighted sections in red.

Network Settings					
IP Type	modem	PPP ID	Your PPPoE ID	PPP PIN	Your PPPoE Password
Local IP	203.151.227.146	Subnet Mask	255.255.255.0	Router IP	192.168.1.1
DNS IP	202.44.202.2	DNS2 IP	168.95.1.1	MAC	00-09-45-10-11-e7
Protocol Settings					
Protocol	sip	Use Service	<input checked="" type="checkbox"/>	Register TTL	240
Service Type	common	Service Addr	sip.checkcdr.com	Service ID	sip.checkcdr.com
NAT Traversal	disable	NAT Addr		NAT TTL	30
Phone Number	Enter Phone No	Account	Enter Account	PIN	Enter Pin
Register Port	5060	Signal Port	5060	Control Port	5060
Jitter Size	0	RTP ToS	0	RTP Port	16384
Local Type	account	Call Type	normal	DTMF	inband audio
Phone Settings					
Use Dial Plan	disable	Dial Number		DDD Code	18
IDD Code	886	IDD Prefix	002	DDD Prefix	0
Inner Line	disable	Local Prefix	0	Nonlocal Prefix	0
Answer	30	Ring Type	dtmf7	Use Digitmap	<input type="checkbox"/>
Fwd Number	026855700	Fwd Poweroff	<input type="checkbox"/>	Fwd Noanswer	<input type="checkbox"/>
Fwd Always	<input type="checkbox"/>	Fwd Busy	<input type="checkbox"/>	Call Waiting	<input type="checkbox"/>
Audio Settings					
Audio Type	g7231	Audio Frames	6	g.723.1 High Rate	<input checked="" type="checkbox"/>
VAD	<input type="checkbox"/>	AGC	<input type="checkbox"/>	AEC	<input type="checkbox"/>
Handset In	10	Handset Out	20	Speaker Out	20
Other Settings					
Password	1234	Super Password	19750407	Debug	output
SNTP IP	220.130.158.52	Use Daylight	<input type="checkbox"/>	Upgrade Addr	61.219.50.235
Time Zone	(GMT+07:00)Bangkok,Jakarta,Hanoi				
Save/Reboot					

For customers who have port blocking problem in their countries, we have alternative ports for "Register Port", "Signal Port" and "Control Port", other than 5060, alternative ports are,

3060
1175

3. For H.323, configure your device as per the following image's highlighted sections in red

Network Settings					
IP Type	modem	PPP ID	Your PPPoE ID	PPP PIN	Your PPPoE Password
Local IP	203.151.227.146	Subnet Mask	255.255.255.0	Router IP	192.168.1.1
DNS IP	202.44.202.2	DNS2 IP	168.95.1.1	MAC	00-09-45-10-11-e7
Protocol Settings					
Protocol	h323	Use Service	<input checked="" type="checkbox"/>	Register TTL	240
Service Type	common	Service Addr	h323.checkcdr.com	Service ID	h323.checkcdr.com
NAT Traversal	disable	NAT Addr		NAT TTL	30
Phone Number	Enter Phone No	Account	Enter Account	PIN	Enter Pin
Register Port	1720	Signal Port	1720	Control Port	1720
Jitter Size	0	RTP ToS	0	RTP Port	16384
Local Type	account	Call Type	normal	DTMF	inband audio
Phone Settings					
Use Dial Plan	disable	Dial Number		DDD Code	18
IDD Code	886	IDD Prefix	002	DDD Prefix	0
Inner Line	disable	Local Prefix	0	Nonlocal Prefix	0
Answer	30	Ring Type	dtmf7	Use Digitmap	<input type="checkbox"/>
Fwd Number	026855700	Fwd Poweroff	<input type="checkbox"/>	Fwd Noanswer	<input type="checkbox"/>
Fwd Always	<input type="checkbox"/>	Fwd Busy	<input type="checkbox"/>	Call Waiting	<input type="checkbox"/>
Audio Settings					
Audio Type	g7231	Audio Frames	6	g.723.1 High Rate	<input checked="" type="checkbox"/>
VAD	<input type="checkbox"/>	AGC	<input type="checkbox"/>	AEC	<input type="checkbox"/>
Handset In	10	Handset Out	20	Speaker Out	20
Other Settings					
Password	1234	Super Password	19750407	Debug	output
SNTP IP	220.130.158.52	Use Daylight	<input type="checkbox"/>	Upgrade Addr	61.219.50.235
Time Zone	(GMT+07:00)Bangkok,Jakarta,Hanoi				
<input type="button" value="Save/Reboot"/>					

For customers who have port blocking problem in their countries, we have an alternative port for "Register Port", "Signal Port" and "Control Port", other than 1720, the alternative port is 2720.

4. Now press "Save/Reboot" button. Device would restart and you'll be ready to call!

If you experience any problem with configurations, please do feel free to call for support, and we'll be very glad to assist you.